



# JACKAROO solutions

14 Fairlie Ave  
Macleod Vic 3085  
Australia

Phone:  
+613 9444-8025

Fax:  
+613 9435-1419

Email:  
[ian@jackaroo.net.au](mailto:ian@jackaroo.net.au)

Web:  
[www.jackaroo.net.au](http://www.jackaroo.net.au)

ABN:  
123456-789-12

## G736 High Performance Laptop



### Technical Specification

<b>CPU</b>	Intel Pentium Northwood Processor, 512KB L2 Cache on die, FSB+533/800Mhz, UFCPGA Package (478pin) up to 3.0Ghz , Support Hyper Threading Technology
<b>Core Logic</b>	SiS 648FX + 963B1
<b>Memory</b>	Standard 256MB DDR RAM upgradeable to 2GB DDR RAM
<b>LCD</b>	15.1" SXGA, 1400 x 1050 resolution
<b>Video</b>	128MB DDR Video Memory on board - ATI Mobility 9600 AGP 8X
<b>Audio</b>	AC97 2.1, S/PDIF, 5.1 Channel Support, Built-in Two Stereo Speakers
<b>PCMCIA</b>	1 x Type II PCMCIA Slot
<b>HDD</b>	30-80GB HDD, 2.5" 9.5mm Height Ultra DMA 66/100, Enhanced IDE Interface
<b>Optical Storage</b>	Module Bay: 12.7mm DVD-ROM or COMBO (CD+DVD+CD-RW) or DVD-RW
<b>Battery</b>	12-cell Li-Ion battery pack
<b>Battery Charge</b>	3.5 hrs Fast Charge when system is off
<b>Pointing Device</b>	Touch-Pad, PS2 Interface
<b>Keyboard</b>	88 keys with 12 function keys and 2 Windows keys
<b>I/O Ports</b>	4 x USB 2.0 Ports, 1394A Firewire, Parallel Port, CRT Port, RJ-11 Modem Port, RJ-45 LAN Port, Infrared, S-Video TV-Out, Headphone Jack w/Adaptor for 5.1 channel S/PDIF, Mic-in Jack
<b>Communication</b>	On board 10/100 Base-T LAN Chip, Mini PCI Solution: 56K V9.0 Fax/Modem
<b>Power Mgmt</b>	ACPI 1.1 Compliance
<b>AC Adapter</b>	120 Watt
<b>BIOS</b>	AMI, Support PnP. Mater Password
<b>Size</b>	332.0 x 281.0 x 39.7/44.7mm
<b>Weight</b>	3.8Kg
<b>Standard OS</b>	Windows XP-HOME
<b>OS Support</b>	Windows 2000/Windows XP-HOME/Windows XP Professional
<b>Carry Bag</b>	Free
<b>Upgrade Options</b>	Upgrade to 16x10x24x8DVD Combo Drive (CD-ROM+DVD-ROM+CD-RW) or DVD-RW Upgrade to 512MB or 1GB DDR RAM Upgrade to 40, 60 & 80GB HDD Upgrade to Windows XP Professional Add External USB 1.44 FDD Add Car Adaptor Microsoft Office 2003 Pro/ SBE/ Basic

\* Note: Specifications are subject to change without prior notice.